

C_I is the I channel conversion loss factor, C_Q is the Q channel conversion loss factor, θ_R is the I-axis phase rotation in radians, B_I is the I channel DC offset in volts, B_Q is the Q channel DC offset in volts, and θ_E is the quadrature phase error in radians.

When the LO and RF frequencies are not equal, θ_R can be set to 0 to simplify (5) and (6):

$$\hat{I}(t) = C_I I(t) + B_I \quad (7)$$

$$\hat{Q}(t) = C_Q (\cos \theta_E Q(t) - \sin \theta_E I(t)) + B_Q \quad (8)$$

θ_R is only important in applications when the phase difference between the RF and LO signals must be known (i.e. phase detector).

Example: Apply a 6 GHz CW LO signal at +5 dBm and a 6.001 GHz CW RF signal at -2 dBm. To estimate the AD60100B's $\hat{I}(t)$ and $\hat{Q}(t)$ signals, start by determining all the parameters in (7) and (8).

C_I and C_Q are determined by the conversion loss and amplitude imbalance of the AD60100B. From the datasheet's typical performance plots at 6 GHz, use 7.3 dB conversion loss and 0.1 dB amplitude imbalance to find C_I and C_Q :

$$\frac{C_I + C_Q}{2} = 10^{(-7.5/20)} = 0.4315 \quad (9)$$

$$20 \log\left(\frac{C_Q}{C_I}\right) = 0.1 \quad (10)$$

$$C_I = 0.429 \quad C_Q = 0.434 \quad (11), (12)$$

Quadrature phase error and DC offsets are also obtained from the typical performance plots at 6 GHz:

$$\theta_E = -0.5 \text{Deg.} = -0.0087 \text{Radians} \quad (13)$$

$$B_I = -0.0025 \text{V} \quad B_Q = -0.002 \text{V} \quad (14), (15)$$

The next step in estimating $\hat{I}(t)$ and $\hat{Q}(t)$ is to calculate the ideal $I(t)$ and $Q(t)$ from the RF input signal. Given that the RF signal frequency is 1 kHz greater than the LO frequency, $I(t)$ and $Q(t)$ define an upper sideband tone of 1 kHz having a constant amplitude of:

$$\frac{A^2}{0.1} = 10^{(-2.0/10)} \quad (16)$$

$$A = 0.2512 \text{V} \quad (17)$$

From (3) and (17) we know:

$$I(t) = 0.1776 \cos(2\pi 1000t) \quad (18)$$

and

$$Q(t) = 0.1776 \sin(2\pi 1000t) \quad (19)$$

The final step in estimating $\hat{I}(t)$ and $\hat{Q}(t)$, the demodulator's real I and Q outputs signals, is to insert (11), (12), (13), (14), (15), (18), and (19) into (7) and (8) giving the final result:

$$\hat{I}(t) = 0.0762 \cos(2\pi 1000t) - 0.0025$$

$$\hat{Q}(t) = 0.077 \sin(2\pi 1000t - 0.0087) - 0.002$$